

PATENT
450100-04961

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE
APPLICATION FOR LETTERS PATENT

TITLE: TAPE LIBRARY APPARATUS AND CONTROLLING
METHOD THEREOF

INVENTOR: Yasunori AZUMA

William S. Frommer
Registration No. 25,506
FROMMER LAWRENCE & HAUG LLP
745 Fifth Avenue
New York, New York 10151
Tel. (212) 588-0800

TAPE LIBRARY APPARATUS AND CONTROLLING METHOD THEREOF

BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates to a tape
5 library apparatus for allowing an apparatus for
recording and reproducing information to and from a
recording medium, namely a so-called drive to be easily
handled and a controlling method thereof.

Description of the Related Art

10 A system that is capable of storing a
plurality of detachable recording mediums (for example,
cassette tapes and disc shaped magnetic recording
mediums) to a recording and reproducing unit
(hereinafter referred to as drive) and recording and
15 reproducing various types of information to and from
the stored recording mediums has been used. The system
is called a library system or auto changer unit.
However, in the following description, the system is
referred to as library system.

20 The library system comprises a cassette
console, a drive console, a conveying unit, a so-called
elevator, a monitor, and a controlling unit. The
cassette console is composed of a plurality of shelves
that hold the forgoing recording mediums. The drive
25 console includes a so-called drive that records and
reproduces information to and from a recording medium.
The elevator is a conveying unit travels among the

cassette console, the drive consol, and so forth and selectively conveys a recording medium from each shelf of the cassette console to the drive of the drive console. The monitor displays the statuses of the individual consoles and the statuses of the drive and the individual shelves. The controlling unit controls the drive and the conveying unit.

[Patent Document 1]

Japanese Patent Laid-Open Publication No.

2000-149516

The Patent Document 1 is directed to a library system would solve troublesome and inconvenient operation of a conventional system that requires the user to input a cassette identifier (ID) of a tape cassette and a bin number to a cassette move window upon traveling the tape cassette from one shelf to another shelf.

The library system uses a fiber channel connected with coaxial cables or optical fiber cables that allows data to be transferred to a host computer at high speed.

For example, as shown in Fig. 1, a host computer 41 and a library system 42 are connected through the Fiber Channel (FC). The library system 42 is composed of a converter 43 and tape drives 44 and 45. In the library system 42, data that is reproduced by the tape drives 44 and 45 is supplied to the

converter 43 through the Small Computer System Interface (SCSI). The converter 43 converts SCSI format data into fiber channel format data and supplies the converted fiber channel format data to the host computer 41.

Since the library system 42 uses the SCSI whose data transfer speed is much slower than that of the fiber channel, the performance of the fiber channel that connects the host computer 41 and the library system 42 cannot be fully used.

In contrast, a library system that has a plurality of tape drives using a fiber channel interface (these tape drives are referred to as FC drives) is known. Each FC drive has been assigned a World Wide Name (WWN) as a unique ID upon production thereof. Since each FC drive has been assigned a WWN that is unique in the world, a WWN that has been assigned cannot be changed after the FC drive was marketed.

However, if an FC drive becomes defective and is replaced with a substitute FC drive, the WWN of the defective FC drive is changed to the WWN of the substitute FC drive.

Since the host computer uses WWNs to manage FC drives, only by replacing the defective FC drive with a substitute FC drive, the substitute FC drive cannot be used. To use the substitute FC drive, it is

necessary to change the management content of the WWNs registered in the host computer and then reboot the host computer.

5 However, if the host computer is mission critical, namely operates 24 hours a day, 365 days a year, it could not be easily rebooted. Thus, the replaceability of a FC drive on site would be very bad.

10 In addition, if the WWN of the substitute FC drive is assigned to the defective FC drive, since the WWN of the defective FC drive has been uniquely assigned in the world upon production thereof, the WWNs of the FC drives should be managed worldwide. Thus, it was difficult to replace a defective FC drive with a substitute FC drive.

15 OBJECTS AND SUMMARY OF THE INVENTION

 Therefore, what is needed is to provide a tape library apparatus for allowing an FC drive to be easily replaced with a substitute FC drive and a controlling method thereof.

20 A first aspect of the present invention is a tape library apparatus to which a node ID is assigned and that is connected to a host computer, comprising:

 a plurality of drives for recording and reproducing data to and from respective large capacity tape recording mediums, the drives having respective
25 interfaces being capable of transferring large capacity data to the host computer,

wherein the drives are assigned respective node IDs as first addresses and respective port IDs that represent mounted order numbers as second addresses and the interfaces are activated.

5 A second aspect of the present invention is a method of controlling a tape library apparatus to which a node ID is assigned and that is connected to a host computer, comprising the steps of:

10 assigning respective node IDs as first addresses and respective port IDs that represent mounted order numbers as second addresses to a plurality of drives for recording and reproducing data to and from respective large capacity tape recording mediums, the drives having respective interfaces being
15 capable of transferring large capacity data to the host computer, and

 activating the interfaces.

 Since the first and second addresses can be assigned to a drive, it can be replaced with a
20 substitute drive without need to reboot the host computer that is mission critical.

 According to the present invention, with an alias WWNN and an alias WWPN that can be assigned to each library system, after a defective FC drive is
25 replaced with a substitute FC drive, it can be controlled and managed with the same WWN as the defective FC drive without need to reboot the host

computer.

According to the present invention, even if an alias WWNN and an alias WWPN that can be assigned to each library system have not been assigned, each FC
5 drive can be used with its unique WWN that was assigned upon production thereof.

[0xxx]

These and other objects, features and advantages of the present invention will become more
10 apparent in light of the following detailed description of a best mode embodiment thereof, as illustrated in the accompanying drawings.

[0xxx]

BRIEF DESCRIPTION OF THE DRAWINGS

15 Fig. 1 is a block diagram describing a conventional host computer and library system;

Fig. 2A and Fig. 2B are schematic diagrams showing a structure of a library system according to an embodiment of the present invention;

20 Fig. 3 is a block diagram describing a connection of a host computer and FC drives according to the embodiment of the present invention;

Fig. 4 is a flow chart describing control for FC drives according to the embodiment of the present
25 invention; and

Fig. 5 is a block diagram describing control preformed by a controlling portion according to the

embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

Next, with reference to the accompanying drawings, an embodiment of the present invention will be described. Fig. 2A and Fig. 2B show an overall structure of a library system according to the present invention. The library system is designated by reference numeral 1. Fig. 2A shows an internal structure of the library system 1 viewed from the front thereof. Fig. 2B shows an internal structure of the library system 1 viewed from one side thereof.

The library system 1 comprises a drive area 11, so-called bins 12, and a cassette conveying unit 13. The drive area 11 has a plurality of FC drives that are recording and reproducing units each of which records and reproduces information to and from a cassette tape. The bins 12 are cassette holding shelves each of which has a plurality of holding portions that are capable of holding a plurality of cassette tapes each. The cassette conveying unit 13 slidably travels on a pair of guide rails 14 between the bins 12 and the drive area 11.

At that point, the cassette conveying unit 13 is controlled by a CPU 16 in accordance with a control signal received from a terminal server 15. Power is supplied to the cassette conveying unit 13 by a power supply portion 17.

In the drive area 11, boards 18 are disposed one every a predetermined number of FC drives. The boards 18 recognize and drive the FC drives. All the FC drives are connected to a fiber channel switch portion 19 with for example respective optical fiber cables. The fiber channel switch portion 19 properly selects the connected FC drives so as to multiplex data reproduced from FC drives on time division basis.

The entire library system 1 is controlled by a controlling portion 20. Power is supplied to all portions of the entire library system 1 by a power supply portion 21. The terminal server 15, the CPU 16, and the controlling portion 20 transmit and receive data through a hub 23.

An input/output port portion 22 is composed of an upper port portion 22a and a lower port portion 22b. The upper port portion 22a and the lower port portion 22b each have a plurality of cassette tape loading and unloading ports. For example, the upper port portion 22a may be a port for loading a cassette tape to the library system 1, whereas the lower port portion 22b may be a port for unloading a cassette tape from the library system 1. A display portion 24 is composed of for example liquid crystal display device.

The FC drives disposed in the drive area 11 have been assigned unique WWNs upon production thereof. According to the present embodiment, when the FC drives

are mounted on the library system 1, besides those
WWNs, other WWNs dedicated for the library system 1 can
be assigned to the FC drives. Hereinafter, the WWNs
dedicated for the library system 1 are referred to as
5 alias WWNs.

According to the present embodiment, the
library system 1 is considered as one node. The node
ID of the library system that has the FC drives is
assigned an alias World Wide Name Node (WWNN). In
10 addition, a plurality of FC drives are considered as
different one-node ports. The FC drives are assigned
unique port IDs as IDs of the FC drives in the mounting
order thereof. Hereinafter, the assigned port IDs are
referred to as alias World Wide Port Names (WWPNs).

15 When a newly mounted FC drive is detected, it
is assigned an alias WWNN and an alias WWPN in
accordance with a control command by the controlling
portion 20. In accordance with the alias WWNN, it can
be easily determined whether or not the FC drive is a
20 newly mounted FC drive. In accordance with the alias
WWPN, it can be easily determined whether or not the
mounted position of the FC drive has been moved.

When an FC drive has not been assigned an
alias WWNN or when an FC drive is not assigned an alias
25 WWNN by the controlling portion 20 (namely, the FC
drive has not been mounted on the library system 1), a
WWN that has been uniquely assigned to the FC drive

upon production thereof is used. Thus, the uniqueness of WWNs can be assured.

The alias WWNN and the alias WWPN are stored in for example a nonvolatile memory disposed in the FC drive.

Next, with reference to Fig. 3, a connection of a host computer and FC drives will be described. The host computer is designated by reference numeral 31. The host computer 31 and the fiber channel switch portion 19 are connected with an optical fiber cable through respective fiber channel interfaces. In addition, the fiber channel switch portion 19 and the FC drives 32 and 33 are connected with respective optical fiber cables through respective fiber channel interfaces. In contrast, the controlling portion 20 and the FC drives 32 and 33 are connected with respective RS-232C cables.

The FC drives 32 and 33 are assigned alias WWNNs and alias WWPNS with respective RS-232C cables by the controlling portion 20. Data reproduced by the FC drives 32 and 33 and data supplied thereto are transmitted and received to and from the host computer 31 through for example an optical fiber cable.

Next, with reference to a flow chart shown in Fig. 4, an example of control for an FC drive will be described. Since the FC drives are controlled in the same manner, the control for each of the FC drive 32,

the FC drive 33, and so forth is the same. Thus, for simplicity, control for only the FC drive 32 will be described in the following.

5 At step S1, the power of the library system 1 is turned on. As a result, the power is supplied to the FC drive 32.

10 At step S2, with a switch disposed for example on the front of the library system 1, it is determined whether or not the library system 1 has been set to a mode in which the library system 1 is used as a library (hereinafter this mode is referred to as library mode). When the determined result represents that the library system 1 has been set to the library mode, the flow advances to step S3. When the
15 determined result represents that the library system 1 has not been set to the library mode, the flow advances to step S5.

20 At step S3, it is determined whether or not a control command has been sent from the controlling portion 20 to the FC drive 32 through the RS-232C cable in a predetermined time period. When the control command has been sent from the controlling portion 20 to the FC drive 32 in the predetermined time period, the flow advances to step S7. When the control command
25 has not been sent from the controlling portion 20 to the FC drive 32 in the predetermined time period, the flow advances to step S4.

At step S4, it is determined whether or not the FC drive 32 has been assigned an alias WWNN. When the FC drive 32 has been assigned an alias WWNN, the flow advances to step S10. When the FC drive 32 has not been assigned an alias WWNN, the flow advances to step S5.

At step S5, the FC interface is set so that the WWN that has been uniquely assigned to the FC drive 32 is used as the address thereof in the library system 1. Thereafter, the flow advances to step S6.

At step S10, the FC interface is set so that the alias WWNN and the alias WWPNN that have been assigned to the FC drive 32 are used as the address thereof in the library system 1. Thereafter, the flow advances to step S6.

At step S6, the FC interface of the FC drive 32 is activated so that the FC drive 32 can be used.

At step S7, it is determined whether or not the control command received from the controlling portion 20 contains a command that causes the FC drive 32 to be rebooted. When the determined result represents that the control command contains a command that causes the FC drive 32 to be rebooted, the flow advances to step S11. When the determined result represents that the control command does not contain a command that causes the FC drive 32 to be rebooted, the flow advances to step S8.

At step S11, the FC drive 32 is rebooted.
Thereafter, the flow advances to step S1.

At step S8, it is determined whether or not
the control command received from the controlling
5 portion 20 contains a command that causes the FC drive
32 to assign an alias WWNN. When the determined result
represents that the control command contains a command
that causes the FC drive 32 to be assigned an alias
WWNN, the flow advances to step S9. When the
10 determined result represents a control command does not
contain a command that causes the FC drive 32 to be
assigned an alias WWNN, the flow advances to step S4.

At step S9, the FC drive 32 is assigned an
alias WWNN and an alias WWPNN. Thereafter, the flow
15 advances to step S10.

Next, with reference to a flow chart shown in
Fig. 5, an example of WWN assigning control performed
by the controlling portion 20 will be described. At
step S21, it is determined whether or not a
20 communication between the controlling portion 20 and
the FC drive 32 has been restored. When the determined
result represents that the communication between the
controlling portion 20 and the FC drive 32 has been
restored, the flow advances to step S22. When the
25 determined result represents that the communication has
not been restored, the flow returns to step S21. At
step S21, the same control is repeated. In other

words, until the communication is restored, at step S21, the same control is repeated.

At step S22, it is determined whether or not the FC drive 32 has been assigned an alias WWNN and an alias WWP. When the determined result represents that the FC drive 32 has been assigned an alias WWNN and an alias WWP, the flow advances to step S23. When the determined result represents that the FC drive 32 has not been assigned an alias WWNN and an alias WWP, the flow advances to step S25.

At step S23, it is determined whether or not the alias WWNN and the alias WWP that have been assigned to the FC drive 32 represent a correct mounted position thereof. In other words, it is determined whether or not the alias WWNN represents a node ID of the library system. In addition, it is determined whether or not the alias WWP represents a correct port ID of the FC drive 32 mounted on the library system. When the determined result represents that the alias WWNN and the alias WWP represent the correct mounted position of the FC drive 32, the flow advances to step S24. When the determined result represents that the alias WWNN and the alias WWP do not represent the correct mounted position of the FC drive 32, the flow advances to step S25.

At step S24, a command that causes the FC interface of the FC drive 32 to be activated is

transmitted as a control command from the controlling portion 20 to the FC drive 32 so that the alias WWNN and the alias WWPN that have been assigned to the FC drive 32 are used as an address of the FC drive 32.

5 At step S25, the alias WWNN and the alias WWPN that represent the correct mounted position of the FC drive 32 are transmitted from the controlling portion 20 to the FC drive 32 through the RS-232C cable.

10 At step S26, a command that causes the FC drive 32 to be rebooted is transmitted as a control command from the controlling portion 20 to the FC drive 32. Thereafter, the flow advances to step S21. After the communication between the controlling portion 20
15 and the FC drive 32 is restored, the FC drive 32 is assigned the WWN that has been uniquely assigned thereto.

20 Although the present invention has been shown and described with respect to a best mode embodiment thereof, it should be understood by those skilled in the art that the foregoing and various other changes, omissions, and additions in the form and detail thereof may be made therein without departing from the spirit and scope of the present invention.

25